

Phonetics and Prowords

Phonetic Alphabet

A	Alpha	J	Juliet	S	Sierra
B	Bravo	K	Kilo	T	Tango
C	Charlie	L	Lima	U	Uniform
D	Delta	M	Mike	V	Victor
E	Echo	N	November	W	Whiskey
F	Foxtrot	O	Oscar	X	X-Ray
G	Golf	P	Papa	Y	Yankee
H	Hotel	Q	Quebec	Z	Zulu
I	India	R	Romeo		

Phonetic Digits

0	ZERO	5	FIFE	DECIMAL	DAY-SEE-MAL
1	WUN	6	SIX	THOUSAND	TOU-SAND
2	TOO	7	SEVEN		
3	TREE	8	AIT		
4	FOW-ER	9	NINER		

Selected Prowords

<p>THIS IS indicates the callsign of the sender is about to follow</p> <p>OVER at the end of a transmission, a reply IS required</p> <p>OUT at the end of a transmission, NO reply is required</p> <p>WAIT OUT your transmission has been received, a reply will follow later</p> <p>MESSAGE a message that requires logging follows</p> <p>SEND you may transmit your message</p> <p>ROGER your message has been received and understood</p> <p>WILCO your message has been received and understood, and I will comply with your instructions</p> <p>SAY AGAIN request for repetition of whole or part of a message</p> <p>I SAY AGAIN indicates you are about to repeat a message as requested</p> <p>UNKNOWN STATION used where the transmission from another station is difficult to read, due to interference or weak signal, resulting in uncertainty regarding their callsign</p> <p>I SPELL the phonetic alphabet will be used to spell a word that may be unfamiliar or difficult to pronounce</p> <p>SLANT indicates an oblique stroke ‘ / ’</p>	<p>FIGURES used before numbers sent digit by digit</p> <p>GRID used before any grid reference encoded or sent in clear speech</p> <p>RADIO CHECK report how you received my transmission</p> <p>EXEMPT callsigns exempted do NOT reply</p> <p>NOTHING HEARD no signal has been received</p> <p>BREAK I am separating the text during a long transmission OR I have finished transmitting to you, and want the next identified station to reply</p> <p>TIME a date/time group follows</p> <p>SPEAK SLOWER request to another station to allow copying of a message</p> <p>READBACK (TEXT) request from the transmitting station to the receiving station to read back the message (or text of the message) to confirm correct reception</p> <p>CORRECT the readback of the message is correct</p> <p>WRONG the read-back of the message is incorrect, and that the message will be repeated</p>
---	---